



PROTAC® RAIL MOUNT HL-X PRO

MULTI-FUEL, HIGH-CANDELA LONG GUN LIGHT



Jack-Cap® provides operational switch redundancy, featuring both a push-button switch and a port for a remote pressure switch



Available Colors:

The ProTac Rail Mount HL-X Pro produces 50,000 candela and shines for 447 meters. Easily replace batteries by unplugging the remote and removing tail cap - no connected wires.

KEY FEATURES

- Jack-Cap® provides operational switch redundancy
- TEN-TAP® programming – Choose from three user-selectable programs: 1) high/strobe 2) high only 3) low/high
- Integrated rail clamp attaches to MIL-STD-1913 (Picatinny) rail or M-LOK® compatible rails

OUTPUT

	HIGH	LOW
LUMENS	1,000	60
CANDELA	50,000	3,100
DISTANCE	447m	111m
RUN TIME CR123A	1.25 hrs	21 hrs
RUN TIME SL-B26	1.75 hrs	24 hrs

Strobe runs 2.5 hours (CR123A) // 3.5 hours (SL-B26)

ITEM NUMBERS

Description	UPC	Item #
ProTac RM HL-X Pro - Includes Jack Cap, M-LOK, momentary switch, mounting hardware and (2) CR123A batteries - Black	080926-88126-6	88126
ProTac RM HL-X Pro USB - Includes Jack Cap, M-LOK, momentary switch, mounting hardware, SL-B26 battery pack and USB Cord - Black	080926-88127-3	88127
ProTac RM HL-X Pro - Light Only - Includes Jack Cap, M-LOK and (2) CR123A batteries - Black	080926-88128-0	88128
ProTac RM HL-X Pro USB - Light Only - Includes Jack Cap, M-LOK, SL-B26 battery pack and USB Cord - Black	080926-88129-7	88129

BATTERY

- Multi-Fuel
- Uses one Streamlight SL-B26 protected Li-Ion USB rechargeable battery pack
- Also, accepts two CR123A lithium batteries

MATERIAL/DURABILITY

- 6000 series machined aircraft aluminum with anodized finish
- Gasket-sealed glass lens
- IP67-rated with standard push-button switch installed (waterproof to 1m for 30 minutes); IP54-rated with remote pressure switch installed (water-resistant)
- 2-meter impact resistance tested

DIMENSIONS

LENGTH: 5.43 in (13.79 cm)

WEIGHT: CR123A 6.6 oz (187.1g) // SL-B26 7.2 oz (204.1g)

WARRANTY

Limited lifetime warranty
Visit streamlight.com for full warranty information

ACCESSORIES

	Description	UPC	Item #		Description	UPC	Item #
	M-LOK® Mount	080926-88300-0	88300		8-Unit SL-B26 Battery Bank Charger without batteries		
					12V DC	080926-20220-7	20220
					120V/100V AC	080926-20221-4	20221
					230V/240V AC	080926-20222-1	20222
	Jack-Cap®	080926-88130-3	88130		8-Unit SL-B26 Battery Bank Charger with batteries		
					12V DC	080926-20223-8	20223
					120V/100V AC	080926-20224-5	20224
					230V/240V AC	080926-20225-2	20225
	Remote Retaining Clips	080926-88178-5	88178		SL-B26 Charger Kit Includes USB cord and (2) SL-B26 battery packs	080926-22010-2	22010
	Straight Latching Pressure Switch	080926-89008-4	89008		120V AC - Includes (2) SL-B26 USB battery packs	080926-22011-9	22011
	Straight Momentary Pressure Switch	080926-69135-3	69135		SL-B26 Charge Cradle	080926-22100-0	22100
	Lithium Batteries 2 Pack	080926-85175-7	85175		Micro USB Cords - for use with charge cradle		
	Lithium Batteries 6 Pack	080926-85180-1	85180		40" (101 cm)	080926-22070-6	22070
	Lithium Batteries 12 Pack	080926-85177-1	85177		22" (55.88 cm)	080926-22081-2	22081
	Lithium Batteries 400 Pack	080926-85179-5	85179				
	SL-B26 Battery Pack 2 Pack	080926-22102-4	22102		120V AC Micro USB Charge Cord (for use with charge cradle)	080926-22071-3	22071
	USB-C cord	080926-22084-3	22084		230V AC Micro USB Charge Cord (for use with charge cradle)	080926-22072-0	22072
					240V AC USB Wall Plug	080926-22049-2	22049

M-LOK® is a registered trademark of Magpul Industries Corp. All rights reserved.
BOROFLOAT® is a registered trademark of SCHOTT AG.