



# PROTAC® RAIL MOUNT HP-X PRO

MULTI-FUEL, HIGH-CANDELA LONG GUN LIGHT



Jack-Cap® provides operational switch redundancy



Securely attaches to long guns with MIL-STD-1913 rails



Available Colors: ●

Get extreme beam reach with 105,000 candela! The multi-fuel ProTac® Rail Mount HP-X Pro shines far and bright, penetrating smoke, fog, and photonic barriers. Its Jack-Cap® tail cap switch offers operational switch redundancy with both push-button operation or remote pressure switch operation.

## OUTPUT

	HIGH	LOW
LUMENS	800	55
CANDELA	105,000	7,600
DISTANCE	648m	174m
RUN TIME SL-B26	2 hrs	26 hrs
RUN TIME CR123A	1.5 hrs	18 hrs

Strobe runs 3.5 hours (SL-B26) // 2.5 hours (CR123A)

## ITEM NUMBERS

Description	UPC	Item #
ProTac Rail Mount HP-X Pro - System - Includes mounting hardware, M-LOK mount, momentary switch, and (2) CR123A batteries - Black	080926-89015-2	89015
ProTac Rail Mount HP-X Pro USB - System - Includes mounting hardware, M-LOK mount, momentary switch, (1) SL-B26 battery pack, and USB cord - Black	080926-89016-9	89016
ProTac Rail Mount HP-X Pro - Light Only - Includes M-LOK mount and (2) CR123A batteries - Black	080926-89017-6	89017
ProTac Rail Mount HP-X Pro USB - Light Only - Includes M-LOK mount, (1) SL-B26 battery pack, and USB Cord - Black	080926-89018-3	89018

## KEY FEATURES

- 105,000 candela
- Jack-Cap® provides operational switch redundancy
- Fits long guns with MIL-STD-1913 rails (optional M-LOK® mount included)

## BATTERY

- Multi-fuel: Uses (1) Streamlight SL-B26® protected Li-Ion rechargeable battery pack or (2) CR123A lithium batteries

## MATERIAL/DURABILITY

- 6000 series machined aircraft aluminum with anodized finish
- Gasket-sealed glass lens
- IPX7-rated with standard push-button switch installed (waterproof to 1m for 30 minutes); IPX4-rated with remote pressure switch installed (water-resistant)
- 2m impact resistance tested

## DIMENSIONS

LENGTH: 5.63 in (14.3 cm)  
 WEIGHT: CR123A 6.4 oz (181g) // SL-B26 7.0 oz (198g)  
 W/ BATTERIES

## WARRANTY

Limited lifetime warranty  
 Visit streamlight.com for full warranty information

ACCESSORIES

	Description	UPC	Item #
	M-LOK® Mount	080926-88300-0	88300
	Jack-Cap®	080926-88130-3	88130
	Remote Retaining Clips	080926-88178-5	88178
	Straight Latching Pressure Switch	080926-89008-4	89008
	Straight Momentary Pressure Switch	080926-69135-3	69135
	Lithium Batteries - 2 Pack Lithium Batteries - 6 Pack Lithium Batteries - 12 Pack Lithium Batteries - 400 Pack	080926-85175-7 080926-85180-1 080926-85177-1 080926-85179-5	85175 85180 85177 85179
	SL-B26 Battery Pack - 1 Pack SL-B26 Battery Pack - 2 Pack SL-B26 Battery Pack - 8 Pack	080926-22101-7 080926-22102-4 080926-22105-5	22101 22102 22105
	40" (101.6 cm) Micro-USB Cord 22" (55.88 cm) Micro-USB Cord	080926-22070-6 080926-22081-2	22070 22081
	SL-B26 8-Unit Bank Charger - 12V DC SL-B26 8-Unit Bank Charger - 120V/100V AC SL-B26 8 Unit-Bank Charger - 230V/240V AC <i>Batteries not included</i>	080926-20220-7 080926-20221-4 080926-20222-1	20220 20221 20222
	SL-B26 8-Unit Bank Charger - 12V DC SL-B26 8-Unit Bank Charger - 120V/100V AC SL-B26 8 Unit-Bank Charger - 230V/240V AC <i>Batteries included</i>	080926-20223-8 080926-20224-5 080926-20225-2	20223 20224 20225
	SL-B26 Charger Kit	080926-22010-2	22010
	SL-B26 Charger Kit	080926-22011-9	22011
	SL-B26 Charge Cradle	080926-22100-0	22100
	120V AC Micro-USB Charge Cord	080926-22071-3	22071
	230V AC Micro-USB Charge Cord	080926-22072-0	22072
	240V AC USB Wall Plug	080926-22049-2	22049

All rights reserved. M-LOK® is a registered trademark of Magpul Industries Corp.